

DISTRIBUTION BOARD	LDB.9
Location Area	Level 9
Servis Area	Level 9
Feeding Circuit Breaker	3x32 A
Feeding cable	5x6 N2XH
User Circuit Breaker	3x32 A
COS ϕ	0,90
Short-circuit current (kA)	5,24

	Power (kW)	Current (A)
Installed	29,90	50,34
Simulation (ks)	0,40	0,40
Demand	11,96	20,13

№	BREAKER №	Line Name	Load Name	DESCRIPTION	faza	Vol tage (v)	Cos ϕ	LOAD POWER (W)				LOAD CURRENT (A)			ELCB	BREAKER	CABLE										I _{kz} (kA)
								sum	L1	L2	L3	L1	L2	L3			Leng th	Instal Method	Corre ction	Wire Size (mm ²)	TYPE		I _z	MAX ΔU%	ΔU%		
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	
1	LDB.9	B1:01	DB.902	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	20	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	0,81	1,31	
2	LDB.9	B1:02	DB.904	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	20	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	0,81	1,31	
3	LDB.9	B1:03	DB.905	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	20	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	0,81	1,31	
4	LDB.9	B1:04	DB.906	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	25	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,01	1,10	
5	LDB.9	B1:05	DB.907	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	25	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,01	1,10	
6	LDB.9	B1:06	DB.908	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	25	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,01	1,10	
7	LDB.9	B1:07	DB.909	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	25	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,01	1,10	
8	LDB.9	B1:08	DB.910	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	30	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,22	0,95	
9	LDB.9	B1:09	DB.911	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	30	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,22	0,95	
10	LDB.9	B1:10	DB.912	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	32	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,30	0,90	
11	LDB.9	B1:11	DB.913	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	32	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,30	0,90	
12	LDB.9	B1:12	DB.914	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	35	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,42	0,84	
13	LDB.9	B1:13	DB.915	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	35	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,42	0,84	
14	LDB.9	B1:14	DB.916	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	40	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,62	0,75	
15	LDB.9	B1:15	DB.917	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	40	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,62	0,75	
16	LDB.9	B1:16	DB.918	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	43	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,75	0,70	
17	LDB.9	B1:17	DB.919	BOARD	1	220	0,90	1 400		1 400			7,07			2P/20A/C/6kA	43	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,75	0,70	
18	LDB.9	B1:18	DB.920	BOARD	1	220	0,90	1 400			1 400			7,07		2P/20A/C/6kA	45	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	1,83	0,67	
19	LDB.9	B1:19	DB.924	BOARD	1	220	0,90	1 400	1 400			7,07				2P/20A/C/6kA	50	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	3,0	2,03	0,61	
20	LDB.9	L1:01	განათება	LIGHT	1	220	0,90	200		200			1,01		2P/16A	1P/10A/B/6kA	75	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	3,0	0,72	-	
21	LDB.9	L1:02	განათება	LIGHT	1	220	0,90	40			40			0,20	2P/16A	1P/10A/B/6kA	45	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	3,0	0,09	-	
22	LDB.9	L1:03	განათება	LIGHT	1	220	0,90	220	220			1,11			2P/16A	1P/10A/B/6kA	110	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	3,0	1,17	-	
23	LDB.9	L1:04	განათება	LIGHT	1	220	0,90	160		160			0,81		2P/16A	1P/10A/B/6kA	50	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	3,0	0,39	-	
24	LDB.9	L1:05	განათება	LIGHT	1	220	0,90	360			360			1,82	2P/16A	1P/10A/B/6kA	75	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	3,0	1,30	-	
25	LDB.9	rezerve	რეზერვი	LIGHT	1	220	0,90	0	0			0,00			2P/16A	1P/10A/B/6kA	0	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	2,5	0,00	-	
26	LDB.9	S1:01	როზეტები	SOCKET	1	220	0,90	700		700			3,54		2P/16A	1P/16A/B/6kA	90	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	2,5	1,83	-	
27	LDB.9	S1:02	რევი	SOCKET	1	220	0,90	1 200			1 200			6,06	2P/16A	1P/16A/B/6kA	55	C	0,78	3x2,5	N2XH	CU-XLPE/XLPE	25,74 A	2,5	1,91	-	
28	LDB.9	S1:03	ფენკოილი	SOCKET	1	220	0,90	420	420			2,12				1P/16A/B/6kA	20	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	2,5	0,41	-	
29	LDB.9	rezerve	რეზერვი	SOCKET	1	220	0,90	0		0			0,00		2P/16A	1P/16A/B/6kA	0	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	2,5	0,00	-	
30	LDB.9	rezerve	რეზერვი	SOCKET	1	220	0,90	0			0			0,00	2P/16A	1P/16A/B/6kA	0	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	2,5	0,00	-	
31	LDB.9	rezerve	რეზერვი	SOCKET	1	220	0,90	0	0			0,00				1P/16A/B/6kA	0	C	0,78	3x1,5	N2XH	CU-XLPE/XLPE	18,72 A	2,5	0,00	-	
								29 900	10 440	9 460	10 000	52,7	47,8	50,5													